

3-20-00

03/17/00  
JC780 U.S. PTO

# BAKER BOTTS LLP

30 ROCKEFELLER PLAZA  
44TH FLOOR  
NEW YORK, NEW YORK  
10112-4498  
212.705 5000  
FAX 212 705.5020

AUSTIN  
BAKU  
DALLAS  
HOUSTON  
LONDON  
MOSCOW  
**NEW YORK**  
WASHINGTON

Appln. Trans.  
PATENT

## UTILITY PATENT APPLICATION TRANSMITTAL

(Only for new nonprovisional  
applications under 37 CFR 1.53(b))

Attorney Docket No. A32894-072797.0127

First Named Inventor ROBERT BEACH

Express Mail Label No. EJ594513708US

Total Pages     

JC542 U.S. PTO  
09/528697  
03/17/00

March 17, 2000

**BY EXPRESS MAIL** - Label No. EJ594513708US

Assistant Commissioner for Patents  
Box Patent Application  
Washington, DC 20231

Sir:

Enclosed herewith for filing is a patent application of ROBERT BEACH entitled IMPROVED WIRELESS  
LOCAL AREA NETWORKS

which includes:

☒ Specification 34 Total Pages  
☒ Claims 16 Total Pages  
☒ Abstract 1 Total Pages  
☒ Drawing(s) 6 Total Sheets  
    X formal  
       informal

☐ Combined Declaration and Power of Attorney      Total Pages  
    ☐ Newly executed (original or copy)  
    ☐ Copy from a prior application  
        (for continuation/divisional only - **must be filed to avoid surcharge for late filing**)

If a continuing application, check appropriate box:

☐ Continuation ☐ Divisional ☐ Continuation-In-Part (CIP)  
of prior application No.     

☐ Amend the specification by inserting, before the first line, the following sentence:

"This is a ☐ continuation ☐ divisional ☐ continuation-in-part  
of copending application Serial No.    filed   ."

Appln. Trans.  
PATENT

Attorney Docket No. A32894-072797.0127

- ☒ An Assignment of the invention to SYMBOL TECHNOLOGIES INC.  
☐ is attached. A separate cover sheet in compliance with 37 CFR 3.28 and 3.31 is included.  
☒ will follow.  
☐ has been filed in the prior application
- ☐ Small Entity Statement(s)  
☐ Small Entity Statement filed in prior application. Status still proper and desired.
- ☐ Information Disclosure Statement (IDS) PTO-1449  
☐ Copies of IDS Citations.
- ☐ Preliminary Amendment
- ☒ Return Receipt Postcard
- ☐ Other \_
- ☐ Cancel in this application original claims \_ of the prior application before calculating the filing fee.

The filing fee has been calculated as shown below:

FOR	(Col. 1) No. Filed	(Col. 2) No. Extra	Small Entity Rate	Fee	OR	Other Than A Small Entity Rate	Fee
Basic Fee							\$690
Total Claims	59	-20 = 39	x \$9 =	\$0		x \$18 =	\$702
Ind. Claims	16	-3 = 13	x \$39 =	\$0		x \$78 =	\$1,014
Multiple Dependent Claim			+ \$130 =	\$0		+\$260 =	
			Total	-			<u>\$2,406</u>

\* If the difference in Col. 1 is less than zero, enter "0" in Col. 2.

Fee Payment Being Made:

- ☒ Enclosed
- ☒ Basic filing fee \$ 2,406.00
- ☐ Recording Assignment  
 [\$40.00; 37 CFR 1.21(h)]
- Total Fees Enclosed \$ 2,406.00

☒ A check in the amount of \$2,406.00 to cover filing fee is enclosed.

Appln. Trans.  
PATENT

Attorney Docket No. A32894-072797.0127

Priority

☐ Priority of application Country   , Appln. No.    filed    is claimed under 35 U.S.C. 119.

☐ Certified Copy of Priority Document(s) Country   , Appln No.   , filed   .

☐ is/are attached ☐ will follow ☐ has been filed in the parent application S/N   .

☒ The Commissioner is hereby authorized to charge payment of any additional filing fees required under 37 CFR 1.16, 1.17, and 1.21(h) associated with this communication or credit any overpayment to Deposit Account No. 02-4377. Two copies of this sheet are enclosed.

Please direct all communications to:

BAKER BOTTS LLP  
30 Rockefeller Plaza  
New York, NY 10112

BAKER BOTTS L.L.P.

By 

James J. Maune

PTO Registration No. 26,946

Enclosures

BAKER & BOTTS, L.L.P.

30 ROCKEFELLER PLAZA

NEW YORK, NEW YORK 10112

---

TO ALL WHOM IT MAY CONCERN:

Be it known that I ROBERT BEACH, a citizen of the United States, residing in Los Altos, California, whose post office address is 1850 Middleton Avenue, Los Altos, California 94204 respectively, have invented an improvement in

**IMPROVED WIRELESS LOCAL AREA NETWORKS**

of which the following is a

**SPECIFICATION**

**BACKGROUND OF INVENTION**

This invention relates to wireless data communications networks, and in particular to arrangements for communications between mobile data handling units and a central computer using wireless data communications.

The assignee of the present invention supplies a wireless data communications system known as the Spectrum 24 System, which follows the radio data communications protocol of IEEE Standard 802.11. In the system as implemented, mobile units are in data communication with a central computer through access points. The access points may communicate with a central computer or computers over a wired network. Each of the mobile units associates itself with one of the access points. The access points in this system are

5 functional to perform all the implemented requirements of the standard protocol, including,  
association and roaming functions, packet formulation and parsing, packet fragmentation and re-  
assembly encryption and system access control. In order to maintain order and reduce radio  
communications each access point must determine which of the data communications received  
over the wired network from the central computer is destined for a mobile unit associated with  
10 that particular access point. This requirement adds significant computational capacity to the  
access point, increasing the cost thereof.

In addition, in applications that must support a high volume of data  
communications from multiple users, such as systems supporting a self-service shopping system,  
15 hospital systems, systems that include paging or voice data links to many users, or systems  
supporting communicating with electronic shelf labels, additional access points are required to  
support the data communications traffic, increasing the overall system cost.

The cost of an operational access point is dependent not only on the complexity  
thereof and the requirement for high speed processing of data pockets for purposes of selecting  
20 those destined for mobile units associated with an access point, but the additional cost of the  
installation of electrical power to the location of the access point, and the cost of a power supply  
to convert AC electrical power to DC power for the circuits of the access point. Further cost may  
be involved in physically mounting the access point hardware and antenna.

In prior systems each access point is connected on an Ethernet wired network to  
25 the central computer. The access points are required to determine the identity of mobile units

5 which have become associated with them and to extract from the data packets on the ethernet network those packets addressed to a mobile unit associated with the access point. This requirement has led to significant processing burden for the access points and led to increased cost for the access points.

10 In the system described in my prior published International Patent Application WO 099 37047, published July 22, 1999, the central computer communicates over an Ethernet wired network with an intelligent switching hub. Alternately a token ring network can be used. The switching hub determines the destination of each packet and routes packets to an access point if the destination of the packet is a mobile unit associated with the access point. To achieve this function, the hub is an intelligent hub which maintains a routing list of mobile units and their associated access point according to the port of the hub.

15 In practice, the hub need only maintain a source list for those access points connected to the hub and mobile units associated with the access points connected to the hub. Thus, if a packet is received at a hub over the ethernet with a destination address which is not associated with that hub, the packet is ignored. The hub will route the packet to an access point only if the destination address of the packet is identified on the list. When a packet is received on a hub port associated with a communications line connected to an access point, the source address is associated with the hub port in the list. The packet is routed either to the ethernet connection or to another port according to the destination address.

20 By determining destination address in the hub and maintaining the association of a mobile unit address with an access point connected to a port of the hub in a routing list of the

5 hub, the functionality required of the access points is greatly reduced. The access point acts  
merely as a conduit sending RF transmissions of packets received on its communication line,  
and receiving transmissions from associated mobile units and providing ethernet packets to the  
hub. In addition, the access point must provide mobile unit association functions and other  
802.11 protocol functions, as provided in the Spectrum 24 system, and may also provide proxy  
10 polling responses for associated mobile units that are in power saving mode.

The prior system may have a large number of access points, each with a memory  
containing program instructions for carrying out the various required functions. This distribution  
of processing makes it difficult to upgrade a system or to provide changes in system  
configuration because any upgrade or change may require changes to the program code in each  
of the access points. Such distribution of processing functions also makes system mangagement  
functions, such as load balancing or access control more difficult.

It is therefore an object of the present invention to provide an improved wireless  
data communications methods and systems having lower cost, to enable the economical  
provision of reliable wireless data communications with increased capacity in complex  
20 installations or at reasonable cost or simple installations.

### **SUMMARY OF THE INVENTION**

In accordance with the invention there is provided a system for providing  
wireless data communications between mobile units and a wired network. The system includes  
25

5 a plurality of RF ports having at least one data interface and arranged to receive formatted data signals at the data interface and transmit corresponding RF data signals and arranged to receive RF data signals and provide corresponding formatted data signal. There is also provided at least one cell controller, arranged to receive data signals from the wired network and to provide formatted data signals corresponding thereto and to receive formatted data signals and to provide data signals corresponding thereto to the wired network, the cell controller controls association of mobile units with one of the RF ports, provides formatted data signals for said mobile units to an associated RF port and receives formatted data signals from the mobile unit from the associated RF port.

15 In accordance with the invention there is provided an improvement in a wireless data communications network coupled to a data processing system, having a plurality of RF ports and mobile units, wherein the mobile units associate with one of the RF data communications ports to conduct data communications with said data processing system. The mobile units are assigned to one of the RF ports by a cell controller, and the cell controller is arranged to receive first data communications from the data processing system and to relay the data communications to an assigned RF port and to receive second data communications from the RF ports and relay the second data communications to the data processing system.

20 In accordance with the invention there is provided a method for operating a wireless local area network having at least one RF port, a plurality of mobile units and a cell controller coupled to the RF port. The RF is operated port to relay signals received from mobile units to the cell controller and to relay signals received from the cell controller to the mobile



5 units. The cell controller is operated to control association of the mobile units with the RF port, including sending and receiving association signals between the RF port and the cell controller, and to send messages to and from the mobile unit via the RF ports.

10 In accordance with the invention there is provided an improvement in a mobile unit for use in a wireless data communications system, wherein the unit has a data processor and programs for the data processor and a wireless network adapter having a programmed processor and a radio module. The programmed processor performs first communications processor functions including control of the radio module and the data processor operates under the programs to perform second communications processor functions, including association with a radio access location of the wireless data communications system.

15 According to the invention there is provided an improvement in a wireless data communications system for providing data communications following a standardized protocol, wherein the protocol includes association of mobile units with radio access locations. At least one RF port is provided at a radio access location, which RF port comprises a radio module and an RF port processor in data communications with a programmed computer. The RF port  
20 processor performs first functions of the standardized protocol and the programmed computer performs second functions of the standardized protocol, including the association of mobile units with said radio access location.

25 According to the invention there is provided an RF port for use in a wireless data communications system comprising a radio module having a data interface and a transmitter/receiver for wireless data communications; and a digital signal processor having first

5 and second data communications ports, random access memory and read-only memory. The second data communications port is coupled to the data interface of said radio module. The read-only memory is provided with a bootloader program for controlling the digital signal processor to load program instructions to the random access memory via the first communications port.

According to the invention there is provided a method for operating an RF port  
10 having a radio module, a digital processor, random access memory and read-only memory. A bootloader program is stored in the read-only memory. The digital processor is operated to download instructions from a computer to the random access memory using the bootloader program and the RF port is operated under the downloaded instructions to send and receive messages using the radio module.

According to the invention there is provided a method for transmitting signals  
15 having a wireless signal format using an RF port having a wired network interface, a data processor and an RF module. Signals are provided to the wired network interface having wireless address data and message data within a data packet addressed to the RF port using a protocol for the wired network. The processor is operated to provide wireless data signals having the wireless  
20 signal format for the address data and the message data to said RF module and operating the RF module is operated to transmit the wireless data signals as an RF signal modulated with the wireless signal format.

According to the invention there is provided a method for transmitting signals  
having a wireless signal format using an RF port having an Ethernet interface, a data processor  
25 and an RF module. An ethernet data packet is provided to the ethernet interface, the ethernet data

5 packet encapsulating as data a data message having the wireless signal format. The data processor is operated to provide the data message to the RF module. The RF module is operated to transmit the data message as an RF signal.

According to the invention there is provided a method for receiving signals having a wireless signal format including wireless address data and message data at an RF port having a wired network interface, a data processor and an RF module. The RF module is operated to receive RF signals having the wireless signal format. The data processor is operated to receive wireless data signals from the RF module and provide data signals to the wired network interface comprising a data packet having a source address corresponding to the RF port using a protocol for the wired network, the data packet including the wireless address data and the message data.

According to the invention there is provided a method for receiving RF message signals having a wireless signal format including an address data format and message data using an RF port having an ethernet interface, a data processor and an RF module. The RF message signals are received in the RF module and provided as data signals to the data processor. The data processor is operated to interpret address data in the data signals and, in dependence on the address data, said message data and said address data is encapsulated in an Ethernet packet, which is provided to the Ethernet interface.

In accordance with the invention there is provided a simplified wireless local area network system including a computer having a data processor and a memory, an RF port having an RF port data processor, an RF module and a data communications interface coupled to the

5 computer. A first program is provided in the memory of the computer for operating the computer data processor to perform first wireless data communications functions, including association with mobile units. A second program is provided for operating the RF port data processor to perform second wireless data communications functions.

10 According to the invention there is provided a wireless access device for providing wireless access to a communication system. The device includes a modem for sending and receiving data messages on the communications system and an RF port, having a data interface coupled to the modem, a data processor and an RF module. The data is programmed to receive data messages from the modem, to format the messages for wireless data communications and to provide the formatted messages to the RF module for transmission by RF data signals to at least one remote station, and to receive RF data signals from the at least one remote station, and to provide data messages to the modem to be sent on the communications system.

15 According to the invention there is provided a method for providing wireless access to the Internet. A modem having a data communications interface connected to an RF port is connected to the Internet. The RF port is configured for wireless data communication to at least one mobile unit having a predetermined wireless communications address. A mobile unit configured with the predetermined wireless communications address is provided for conducting RF data communications with the RF port. The RF port is arranged to relay communications between the mobile unit and the modem.

25 The apparatus and methods of the present invention provide RF ports as radio

5 access locations which are less expensive than known access points and provide greater system management and flexibility. Much of the software used for controlling communications to and from mobile units is performed in a controller wherein software upgrades and changes are easily implemented. According to some embodiments, wherein instructions are downloaded to RF ports, it becomes easy to upgrade RF port instructions. System control is centralized, making management easier and enabling changes to access control and encryption functions. Priority for traffic purposes can also be established to facilitate digital telephony by giving priority to voice traffic. Accordingly, a system is provided that has significant flexibility using common RF port hardware to provide a wireless LAN having from one to hundreds of radio access locations.

10 For a better understanding of the present invention, together with other and further embodiments thereof, reference is made to the following description, taken in conjunction with the accompanying drawings, and its scope will be pointed out in the appended claims.

#### **BRIEF DESCRIPTION OF THE DRAWINGS**

15 Figure 1 is a block diagram of a wireless communications system in accordance with the present invention.

20 Figure 2 is a block diagram illustrating one example of a mobile unit arranged to be used in the system of Figure 1.

Figure 3 is a block diagram illustrating one example of an RF port for the system of Figure 1.

25 Figure 4 is a more detailed block diagram of a preferred embodiment of an RF port in accordance with the invention.

5                   Figure 5 is a block diagram of an arrangement of a computer and RF port for providing a simplified wireless local area network according to the present invention.

                  Figure 6 is a block diagram of an arrangement for providing wireless access to the Internet using the RF port of the present invention.

                  Figure 7 is a diagram showing signal format according to one embodiment of the  
10                  invention.

### **DESCRIPTION OF THE INVENTION**

Referring to Figure 1, there is shown an example of a wireless data communications system 10 according to the present invention for providing data communications between a central computer or a collection of computers on a wired network 16 and a plurality of mobile units 20. While prior systems used access points at each radio access location, where the access points are capable of managing wireless communications with mobile units, the system of Figure 1 uses simplified RF ports 18 at each radio access location to provide radio packet communications with the mobile units 20 using a wireless communications protocol, such as IEEE Standard 802.11, whereby the radio modules in the mobile units 20  
15                  monitor polling signals from the RF ports 18, which are originated by the cell controllers 14 and associate with an RF port 18 for purposes of data communications. The system arrangement of Figure 1 is especially effective in a large wireless local area network (LAN) system wherein it may be necessary to provide a large number of radio access locations. Typically such systems, operating at low power microwave frequencies, require radio access locations at about every 100  
20                  feet. Where the wireless LAN system must operate with mobile units, for example, portable  
25                  feet. Where the wireless LAN system must operate with mobile units, for example, portable

5 computers or similar devices, located throughout a large facility, such as a business, hospital  
complex or university campus, many such radio access locations may be required, possibly  
several hundred. Accordingly there is an incentive to reduce the cost of the installation at each  
radio access location. According to the present invention the system configuration and operation  
are redesigned to reduce the cost of each individual radio access point. In addition, the system of  
10 the present invention provides a concentration of operational control in one or more central  
controllers 14, making management of the system easier and making modifications and upgrades  
easier to install..

According to the invention, much of the functionality of the 802.11 protocol  
associated with the conventional access point, is removed from the device located at the radio  
access location and provided in a cell controller 14, which may be located in conjunction with a  
switching hub 12, connected to the wired network 16, with which the wireless network 10 is  
associated. In particular the usual "access point" device is replaced with a simpler device 18,  
herein referred to as an "RF port" which contains the RF module, which may be the same RF  
module used in the prior art access point, and simplified digital circuits to perform only a limited  
20 portion of the 802.11 media access control (MAC) functions performed by the prior art access  
point. In particular the RF port 18 preferably performs only functions of the access point that  
require a lower level of processing resources in terms of processor capacity and software  
complexity (memory requirement), and which are time critical. Other functions that are more  
processor intensive and require more complex programming, and which are not time critical, are  
25 relegated to one or more "cell controllers" 14, which may perform these more complex functions

5 for a plurality of RF ports 18.

In order to perform the higher level processing functions of the access point in the cell controller 14, according to the present invention, all messages directed to or from mobile units 20 associated with a particular RF port 18 are processed in a cell controller 14. A system may have one or more cell controllers, which may comprise, e.g. Pentium-type board level computers, each of which is arranged and programmed to handle data message traffic and mobile unit associations for a selected plurality of RF ports 18. A switching hub 12 may be interposed to provide message switching among the wired network connected to communications line 16, RF ports 18 and cell controllers 14. Each of the one or more cell controllers 14 acts as a virtual “access point” for traffic addressed to its associated RF ports 18 and to the mobile units 20 associated with those RF ports. When a message is addressed to a mobile unit 20 is received on line 16, switching hub 12 directs the message to the appropriate cell controller 14, which reformats the message and relays the message to the appropriate RF port 18, again through switching hub 12. When the message is received by an RF port 18, it is converted to a radio message and sent to the mobile unit 20 with a minimum of processing.

Likewise, when a message is received from a mobile unit 20 by an RF port 18, it is converted to a digital message packet and relayed to the cell controller 14 associated with the RF port 18 through the switching hub 12. The cell controller 14 parses the message for further relay in the system.

An important feature of a preferred embodiment of the invention is the fact that mobile unit association with the RF ports 18 is a function handled by the cell controller 14.



5 Accordingly, when a mobile unit 20 first becomes active, it sends an association request signal in response to a beacon signal sent by an RF port 18 (in response to direction by the cell controller). The association request signal is relayed by the RF port 18 to the cell controller 14, which performs the processing required for association, including consideration of RF port loading. Cell controller 14 generates appropriate response signals to be sent by the RF port 18 to the mobile unit 20. The cell controller 14 is in an appropriate position to evaluate the loading of the RF ports 18 under its control, and may therefore easily perform load leveling functions, for example, by providing a message to RF port 18 accepting or declining an association request. In addition, the cell controller 14 may receive load messages from other cell controllers 14 in the system 10 and thereby coordinate overall load management. As a mobile unit 20 moves from a location serviced by one RF port 18 to a location serviced by a different RF port 18, the cell controller 14 receives information from the mobile unit 20 indicative of its reception of beacon signals from the various RF ports in the system and performs the necessary functions to support roaming of mobile unit 20.

While in the system 10 of Figure 1 the cell controllers 14 are shown as separate computers connected to switching hub 12, the term "cell controller" is intended to refer to the logical functions performed by these computers rather than the computers themselves. As will become apparent, the cell controller may be implemented in a variety of ways other than as shown in the exemplary system 10 of Figure 1.

Implementation of a simplified RF port is achieved by performing "higher level" functions of the 802.11 protocol Media Access Control (MAC) in the cell controller and

5 performing “lower level” functions in a simplified RF port.

The lower level functions are those that are hardware intensive and often time critical. The higher level functions are those that are software intensive and not time critical. One possible division of the exemplary 802.11 MAC functions is as follows:

Lower Level Functions (preferably to be performed at RF port)

- Cyclic Redundancy Check (CRC)
- Network Activity Vector (NAV)
- Ready to Send/Clear to Send (RTS/CTS)
- Header generation/parsing
- Collision Avoidance
- Frequency Hopping
- Ack parsing/generating
- Retransmission timeout

Higher Level Functions (preferably to be performed at Cell Controller)

- Association processing
- Roaming
- Retransmission
- Rate Control
- Host Interface

The following optional (higher or lower) level MAC functions can be placed in either the higher or lower level categories.

5

Wired Equivalent Privacy encryption/decryption (WEP)

Fragmentation/Reassembly

Data Movement

Power Save Polling Support (PSP)

10

According to a preferred arrangement of the system of the invention, the lower level MAC functions are provided at the RF port , the higher level MAC functions are provided in the cell controller and the optional level functions can be provided at either the cell controller or the RF port.

15

A major advantage of the invention is a cost savings in hardware, processor capacity and storage capacity for the RF port. Since a system with, for example, one hundred or more radio access locations may be implemented with one or two cell controllers, the processor hardware and memory required for the higher level MAC functions need be provided only at the cell controllers. In fact, the capabilities of the overall system, for WEP encryption and other special functions, can be increased at modest cost by using a high performance board level personal computer or even a host computer as a cell controller.

20

By eliminating the higher level MAC functions from the radio access locations, the cost of the devices installed at those locations can be significantly reduced because of lower processor capacity and storage.

25

In connection with association and roaming functions the RF ports 18 provide beacon signals in response to commands generated by the cell controller 14. When an association sequence is initiated by a mobile unit, the RF port 18 relays the association messages

5 between the mobile unit 20 and the cell controller 14 during the association process, which is handled by the cell controller 14.

10 In connection with message traffic to a mobile unit 20 from a network processor, message packets are routed by switching hub 12 to the cell controller 14 responsible for the mobile unit 20 addressed. The message is buffered and formatted by the cell controller 14 and in a preferred arrangement encapsulated by the cell controller 14 as a mobile unit packet within a wired network packet addressed to the responsible RF port 18. This packet is routed to the RF port 18. The RF port 18 extracts the mobile unit packet from the message and sends the packet to mobile unit 20 as a radio signal. The RF port 14 may also provide a CRC calculation and generate CRC data to be added to the message. The mobile unit 20 responds with an acknowledgment signal to the RF port 18, which generates and sends an acknowledgment status message to cell controller 14.

15  
20 In connection with messages for systems connected to the wired network 16, the mobile unit 20 sends a packet to the RF port 18 by radio signal. The RF port 18 filters received radio message packets according to the BSS (Basic Service Set) identifier in the packet and, if the packet has a BSS identifier associated with the RF port 18, performs the CRC check as the packet is received. The RF port 14 then generates and sends an acknowledgment signal to the mobile unit 20 and sends the received packet to cell controller 14. Cell controller 14 buffers, parses and, if necessary, decrypts the packet and routes the packet to the host on network 16 through hub 12.

25 The arrangement of RF port 18 may be identical to current access points used in

5 the Spectrum 24 system with some of the access point software non-functional. Preferably the  
RF ports are simplified to reduce cost and power consumption. To reduce installation expenses  
the RF ports are powered via an ethernet cable, which also connects RF ports 18 to switching hub  
12 or to cell controller 14. The RF ports can be arranged in a small package (e.g. portable radio  
size) with integrated diversity antennas and arranged for easy mounting, such as by adhesive tape  
10 or Velcro. Connection to the switching hub 12 is by ethernet cable which is also provided with  
D.C. power, such as by use of a choke circuit, such as Pulse Model PO421 as described in my  
referenced International Application. The choke circuit may be built into an ethernet connector  
and is available in this configuration.

15 The RF port 18 does not have to perform ethernet address filtering and does not  
have to perform 802.11 association and roaming functions and can therefore have a lower level  
of processor capacity, software support, memory and power consumption. In one embodiment  
shown in Figure 3 the RF port 18 includes only a digital signal processor (DSP) 38 which  
includes internal RAM and ROM. The DSP 38, which may be one of the Texas Instruments  
TMS 320 family of DSP processor, such as the 5000 series, specifically the TMS 320 UC 5402  
20 or the TMS 320 VC 5402. This DSP provides an interface between the ethernet cable 46 and the  
RF module 42 in RF port 18, as shown in Figure 3. The RF module 42 is provided in housing 36  
with DSP 38, DC/DC power supply 40 and carrying one or more antennas 44. RF module 42  
includes a 3860 or 3861 baseband processor, such as HFA 3860B, to interface with the digital  
portion of the RF port 18, specifically DPS 38. In one arrangement the ROM memory of the  
25 DSP 38 can be provided with "bootloader" firmware that downloads the necessary DSP software

5 instructions from the cell controller 14 upon startup of the RF port 18, and loads the instruction into the RAM of the DSP 38.

The processors that are currently preferred as a possible lower level MAC engine are the TMS320UC5402 and the TMS320VC5402. These parts are functionally identical except for  
 10 differences in power consumption (the VC5402 is currently in production and while the UC5402 is still being sampled). The basic configuration of the UC5402/VC5402 is:

- 100 MIPS execution rate
- 8 KB on chip ROM (organized as 4K x 16 bits)
- 15 - 32KB on chip RAM (organized as 16K x 16 bits)
- Two 16 bit timers with 1  $\mu$ s or better resolution
- Two High speed, full duplex serial ports (up to 50 Mbits/sec each) with smart DMA channel support
- One High speed 8 bit wide host/parallel port (160 Mbit/sec)
- 20 - Six DMA channels for general purpose use
- 16 bit external memory/IO Bus with internal wait state generation
- 16 interrupts with 3 instruction (30ns) worst case latency
- 0.54 mW/MHz power consumption (30mA@1.8v at 100 MHz)
- Low Power Modes (6mA, 2mA, 2 $\mu$ A depending on setting)
- 25 - Internal PLL that generates the system clock with an external crystal

5                   This section will describe the use of a 5402 DSP 38 as a MAC engine for 11 Mbit/sec 802.11 DS systems. It could clearly be used in FH systems as well. We will focus on the how the 5402 interfaces to the Intersil 3860/1 baseband processor in RF module 42 and how it implements the lower level MAC functions.

10                   The first issue is how the 5402 DSP 38 interfaces to the 3861 (much of what is said applies to the 3860 as well) and the rest of the RF module 42. As shown in Figure 4, the 3861 processor 53 in RF module 52 of RF port 50 has 2 major interfaces, both serial. The first interface, labeled DATA, is used to transfer data between the MAC engine comprising DSP 64 and the 3861. It has four lines: TxD, TxC, RxD, and RxC and operates at up to 11 Mbits/sec. The exact rate depends on the transfer rate of the packet. The clock signals of both interfaces are  
15                   generated by the 3861 and so transfers are controlled by the 3861. Both can be halted at any time by the 3861 as well as change rate. The second serial interface, labeled CONTROL is used to load commands into the 3861 and read status information from the 3861. This interface is a 4 wire bidirectional interface using one data line, one clock line, one "direction control" line, and a chip select line. This serial interface also can operate at up to 11 Mbits/sec. In addition to the  
20                   serial interfaces, there are additional control and status lines such as Reset, TX\_PE, RX\_PE, TX\_RDY, etc..

                  The 5402 DSP 38 has two sets of full duplex serial interfaces that are capable of operation up to 50 Mbits/sec (given a 100 MHz clock). They can be clocked using internal or external sources. In this design one of the sets of serial interfaces, labeled SER1, is used to  
25                   connect to the high speed data lines of the 3861 interface 53. The 5402 DSP 38 interfaces have

5 the same basic lines (RxD, RxC, TxD, TxC) as does the 3861 and so they connect with minimal trouble. Although the 5402 uses 1.8v for its core, its I/O lines are 3.3v tolerant and so can interface to the 3861 without converters. In addition, they are fully static and so can deal the start/stop operation of the clock lines from the 3861.

10 Data transfer will be done under DMA control within the 5402 using what TI calls “Auto Buffering Mode.” This provides essentially dedicated DMA channels for each serial port interface (two DMA channels per serial port interface). These channels access an independently operating bank of SRAM and so transfers have no impact on CPU performance. The CPU can start transfers in either direction and be notified via interrupt on their completion.

15 Interfacing to the control serial port on the 3861 interface 53 can be done in three different ways. The first, illustrated in Figure 4, utilizes the second serial port, labeled SER 2 on the 5402 DSP 64 with a small amount of combinatorial logic/buffering to convert between the single data line of the 3861 and the dual data lines of the 5402. Another approach is to use an external shift register that would perform serial/parallel conversion. This register would sit on the I/O bus of the 5402 and would be loaded/read by the 5402 and data shifted between it and the 20 3861. The third approach is to use an external buffer/latch on the 5402 I/O bus and “bit bang” the clock/data lines to the 3861. The second or third approaches free up the second serial channel for more other use such as providing high speed serial interfaces such as ethernet or USB and in some applications would be preferred over the first. All require a small amount of external combinatorial logic and so the cost of all solutions is about the same.

25 The same logic would apply to interfacing to the synthesizer. It is accessed even



5 less often than the control port of the 3861 and so a "bit banging" approach would work fine.

Finally, interfacing to the various control and status lines presented by the 3861 can be done via simple bidirectional register/latch connected to the I/O bus of the 5402. The 5402 can read/write this register as it needs to control and monitor the 3861. It would be possible to combine all control/monitor functions (including the serial control interface) into a single 16  
10 bit buffered register latch. Parallel control/status lines would be connected to particular lines of this latch. Serial control interfaces would also be connected and "bit banged" as necessary to move data between the 5402 and 3861.

The arrangement shown in Figure 4 uses a Crystal CS 8900 A ethernet controller 63 coupled to the parallel port of DSP 64 to interface to the ethernet port 58. An ethernet connector/choke 58 receives cable 60 and provides DC power from cable 60 to DC/DC power supply 62. The Figure 4 RF port 50 includes spaced diversity antennas 54, 56 to improve reception in multipath conditions.

A premise of this design is that the TI DSP is capable of implementing all lower level MAC functions without external hardware assistance. This, of course, is the most  
20 demanding model but we will find that the 5402 is up to the task. The most computational demanding tasks are the CRC-32 and WEP processing. The CRC-32 calculation is performed over the entire packet and must be completed in time to generate an ACK should the CRC turn out to be correct (or to attach the calculation result to an outgoing packet on transmission). This means that the CRC calculation must be performed in near realtime during packet transfer  
25 between the 3861 and 5402. TI has shown in an application note that a CRC-32 calculation can

5 be made by a 5000 series DSP in 13 instructions. At 100 MIPS this is about 130ns. At 11  
Mbit/sec, a byte takes about 770ns to transfer and so we have plenty of time to do the CRC.  
When receiving a packet, the serial port would be transferring the data from the 3861 to SRAM  
within the 5402. At the same time the CPU within the 5402 would be reading each received byte  
from SRAM and calculating the CRC. It would of course have to make sure that it did not  
10 overrun the receive buffer, but that would be a relatively simple task. Much the same process  
would happen during transmission. In either case, the CPU has lots of time to do the CRC.

The WEP processing if performed in the RF port 50, is a harder function to  
perform than CRC-32 since it includes both an RC4 encryption function and a second CRC-32.  
At the same time it does not need to be completed prior to ACK generation/reception nor is  
15 performed on every packet (just data packets). The RC4 encryption function consists of two  
parts: building the encryption table (a 256 byte table) using the selected key and doing the  
encryption/decryption process. Based on sample code, it is estimated that building the table  
would require about 1200 instructions (12ms at 100 MIPS) and the encryption/decryption  
process would require about 12 instructions/byte. There is no difference in this cost for 40 or  
20 128 bit keys. The WEP CRC-32 would require another 13 instructions per byte.

The per byte computational burden for WEP would thus be about 25 instructions  
or about 250ns at 100 MIPS. When added to the packet CRC-32, the total load would be around  
38 instructions/byte. As we pointed out, at 11 Mbit/sec we have about 77 instructions/byte  
available, so we are spending about 50 % of the CPU on CRC/WEP tasks. The biggest issue is  
25 the 1200 clocks (12us) required to build the encryption table during receive (For transmission,

5 the calculation can be done prior to starting packet transfer). Pausing to create the table would  
put the CPU about 18 bytes (12us at 770ns/byte) behind in the CRC/WEP/CRC calculation  
process. It would require about 40 data bytes to catch up (1200 clocks/ 30 extra clocks per byte)  
in both packet CRC and WEP/CRC functions. Since the minimum TCP/IP header is at least 40  
bytes (plus any user data), we should have enough time. In any case if we are a little late in  
10 WEP/CRC calculation, no harm is done. An alternative approach would be to catch up first for  
the packet CRC calculation and then catch up with WEP/CRC.

After CRC and WEP/CRC processing, the next most critical activity is header  
parsing on receive and generation on transmit. This is because of the need to identify packets for  
the station and generate appropriate responses. On receive, the processor must parse two or three  
15 48 bit addresses and at least a 16 bit header command field. After the packet completes, an ACK  
may need to be generated.

The 5402 can easily handle these functions. Since these functions are performed  
prior to WEP processing, the CPU has 64 instructions/byte (77-13) to perform these functions.  
Since many of them can be performed on a 16 bit or even 32 bit basis (the 5402 supports both 16  
20 and 32 operations), there may be up to 128 or 256 instructions per data item (i.e. 256 instructions  
to perform a 32 bit address check). These functions are performed at 2 Mbit using a 1 MIPS 188  
CPU. We have a 100 MIPS CPU to do the same tasks at 11 Mbit/sec.

ACK generation is likewise relatively simple. An ACK frame is only 14 bytes  
long, including the 4 CRC-32. Given there is a long (80us) preamble, we have 8000 instructions  
25 to prepare the ACK. The same applies to RTS/CTS exchanges.

5           There are two 16 bit timers available on the 5402. In this model, one would be  
used for TSF timing and the other for all other functions. There are really only a few other timer  
functions: NAV, Retransmission, collision avoidance slot countdown, etc.. Retransmission and  
collision avoidance activities go on only when waiting for an ACK or to start a retransmission  
after detection of an idle network. In such cases there is no data transfer going on and so there is  
10   lots of CPU cycles available.

Support for MU PSP function can be done in a variety of ways, depending on how  
much, if any, external hardware is provided. The 5402 provides a variety of means of conserving  
power. The first is simply to slow down the CPU clock via the software controlled PLL within  
the unit. The 5402 generates internal clocks via a PLL that is driven by either an external crystal  
or clock. The PLL multiplies the base frequency of the crystal/external clock by a factor  
15   determined by software. Hence one means of controlling power consumption is simply to slow  
down the CPU clock. Since the CPU portion of the processor consumes most of the power,  
slowing it down has the biggest affect on power consumption.

The second approach is use one of the IDLE modes of the processor. IDLE1 stops  
20   the CPU clock entirely but leaves everything else running. Power consumption in this mode is on  
the order of 6mA at 100MHz. The CPU can be restarted by any interrupt (internal or external). In  
IDLE2 the system clock is stopped and this reduces consumption to 2mA. In IDLE3, all system  
functions are stopped and consumption is reduced to around 2ua. In all cases all state is retained.  
In IDLE2 and IDLE3, an external interrupt is required to restart the CPU. In such cases an  
25   external, low power timer would be required.

5           Thus with no external hardware, power consumption could be reduced to at least 6mA and perhaps less. With a simple external timer, one could get down to microamps.

          The bottom line is that the vast CPU power of the 5402 allows all lower level MAC functions to be performed in software. Furthermore it has sufficient power and memory to handle additional "higher level" functions such as packet retransmission, fragmentation, and  
10       reassembly that can also be done in a cell controller.

          The system 10 of the present invention is compatible with IEEE Standard 820.11 and accordingly will operate with any mobile units 20, including existing units, which are compatible with the same standard. However, the improvements applied to the RF ports 18, reducing the complexity and cost of these units can also be applied to the mobile units 20, which  
15       have sufficient main processor capacity to handle the mobile unit functions corresponding to the higher order MAC functions.

          Referring to Figure 2 there is shown a block diagram for a mobile unit 20 having a mobile unit computer 22 and a WLAN adapter 24 connected thereto to provide wireless communications to the system 10 of Figure 1. In the mobile unit 20 of Figure 2, the lower level  
20       MAC functions are performed in WLAN adapter 24, which also includes RF module 28 and antenna 29. The configuration of WLAN adapter 24 may be similar to existing adaptors, but preferably adapter 24 is simplified to perform only the lower level MAC functions of the IEEE 802.11 protocol and allow special software 34 in host computer 22 to perform the higher level MAC functions, such as association and roaming. In a preferred arrangement the MAC functions  
25       of adapter 24 are performed in a digital signal processor 26, as described below, which may be

5 the same type DSP described with respect to RF port 50.

This section addresses how the 5402 DSP could be used as a MAC engine in Mobile Unit configurations. There are two considerations in building MU WLAN solutions. The first is the location of those MAC functions, while the second is the physical interface to the host.

10 The location of the upper level MAC functions may vary considerably. Some possibilities are:

- All functions on MAC engine DSP processor 26
- All functions on host processor 22
- Roaming/association on host processor 22, rest on MAC engine 26
- 15 - Roaming/association/retransmission on host 22, rest on MAC engine 26. The choice of the location of the higher level MAC functions has a major impact on the cost of MU WLAN adapter. If one is willing to place at least some of the higher level functions on a host processor 22, then one could get by with just the 5402 on the WLAN adapter. Possible functions to place on the host would be roaming and association control. Higher level functions such as

20 retransmission and fragmentation/reassembly could be left on the 5402. This split would permit significant savings, since another processor/memory subsystem would not be needed on the WLAN adapter. There are two reasons for not placing all of the MAC functions on the 5402. The first is memory space on the 5402 is only 32KB of SRAM for both code and data. In some MAC implementations such as frequency hop, the code space alone exceeds 32 KB. The second reason  
25 is that the software on the 5402 is oriented toward meeting hard, realtime tasks such as CRC and

5 WEP processing. Trying to add software intensive tasks would only complicate the process.

If another processor was required, such as an ARM or perhaps a second 5000 Series processor, the upper level functions could be added to it.

Alternatively one could place all the MAC functions on a faster and/or bigger version of the 5402 processor. Such a processor would likely have a higher clock rate (current  
10 members of the 5000 Series can be clocked as high as 160 MIPS) and more memory ( say 64 KB instead of 32KB).

Both the second processor as well as a faster/bigger 5402 would consume additional power as well as adding cost.

15 This section will describe one approach of how a MU WLAN adapter can be arranged for various hardware host interfaces using the 5402. It assumes that enough of the upper level MAC functions have been offloaded to a host processor so that only the 5402 is required on the PLAN adapter. A second processor could be added to any of the solutions outlined below.

In all of the following solutions, it is assumed that the runtime code for the 5402  
20 is loaded from an external source (such as computer 22) via the host interface 32. This eliminates the need for flash memory on the adapter card, saving several dollars in the process. It should be pointed out that the 5402 comes with 8KB of mask programmable ROM and a bootloder program (required for the USB and Ethernet host interfaces) would be placed in it. The bootloder would be smart enough to download the runtime code instructions over whatever  
25 serial interface was available.

5

The simplest interface of all would be for a host to use the Host Port on the 5402.

10

This port operates as a dual port interface into the memory within the 5402. It would not be a standard interface but would be quite suitable for dedicated systems. Using it, computer 22 can read/write memory on a random or sequential basis. It is an 8 bit interface and can operate as fast as 160 Mbit/sec. When operated in random access mode, the computer 22 generates a 16 bit address using two writes to the port and then performs either a read or write operation. Such a mode allows a host to set up command blocks and the like within the memory of the 5402. Sequential mode allows a host to transfer data in and out of the 5402 memory very quickly (160 Mbit/sec). This would be used for transferring data.

15

If this approach was used, the only digital component on the WLAN adapter would be the 5402.

20

In the system of Figure 1, the cell controller 14 is a board level personal computer coupled to the switching hub 12 preferably by 10 M bit and 100 Mb Ethernet ports. For smaller systems a 350 MHz Pentium computer with 16 MB RAM may be used. For larger systems having many RF ports a 500 MHz Pentium with 64MB RAM is appropriate. Communications to and from the wired network are preferably carried out at 100 MHz. Communications to and from RF ports may be carried out at 10 MHz. A second cell controller may be supplied for larger systems and/or to provide backup in the event one cell controller fails. Reliability can be enhanced by providing dual fans and dual power supplies. A flash disk memory may be used for reliability. Alternately, the cell controller 14 may be built into the switching hub 12 or into a host processor.

25



5           The operating system for the cell controller 14 may be a real time operating system, such as VRTX or QNX, which provides multitasking, a full network stack and utilities. Web based management utilities, which are client side java based, are provided for maintaining the configuration of the cell controller 14, the RF ports 18 and status of the mobile units 20.

10           The cell controller 14 includes applications to provide mobile unit association management, roaming and packet buffer management. These applications are similar to those performed by current access points in the Spectrum 24 system. The cell controller 14 may also provide QoS support, user authorization and configuration management. Placing these functions on a personal computer cell controller facilitates system management and program updates using available programming tools. Further, modifications to authorization or management functions need only be installed into the cell controller 14, and no modification to the software of the RF ports 18 is required.

15           The cell controllers 14 handle routing of all messages to or from the mobile unit. The cell controller buffers message packets received from the wired network and determines the appropriate RF port 18 with which the addressed mobile unit 20 is associated and sends the packet to the RF port 18. The cell controller 14 can additionally perform WEP encryption/decryption and the CAC associated therewith.

20           The cell controller 14 may also the additional function of maintaining and downloading firmware to the RF ports 18. Upon power up the RF ports 18 use a bootloader routine stored in ROM to send a download request to cell controller 14. The cell controller then  
25           downloads firmware to the RF port 18, including configuration information such as channel

5 assignment, ESS and BSS identification. The cell controller 14 and RF ports 18 additionally share a common TSF clock.

The mobile unit computer 22 of mobile unit 20 is provided with similar software to perform the higher level MAC functions as outlined above. Advantageously, the software 34 can be programmed using the same operating system as provided for the computer, and thereby provide a user interface, such as Windows, which is familiar to the user. The mobile unit software 34 provides the MAC functions of header building, roaming and association. The mobile unit computer 22 may also download firmware to the processor in the WLAN adapter 24.

As evident from the forgoing description, the hardware for RF port 18 and WLAN adapter 24 of mobile unit 20 can be substantially similar, with the possible exception of the interface to an Ethernet network or to a mobile unit host. Further, the logical cell controller function and the higher order MAC functions performed by the mobile unit host processor can be performed on any computer system.

Using the RF port 18 of the present invention coupled to a computer system, it is possible to provide either a mobile unit or a wireless network according to the software provided. Since the software for RF port 18 may be downloaded from a host system a simple combination of a computer and one or more RF ports can function as either a WLAN mobile unit as a WLAN host or both, by providing function selectable firmware to the processor in the RF port.

In the arrangement shown in Figure 5, a personal computer 70 is provided with software 72 and connected to one or more RF ports 50A, 50B to provide a complete host system

5 for wireless data communications. This arrangement could be used, for example, in a small business wherein office equipment is connected to server 70 by a wired network for conventional LAN operation and one or more RF ports 50 are also connected to server 70 on the LAN system to provide data communications between the server 70 and mobile units. The server can perform the higher order MAC functions and download firmware instructions to the RF ports.

10 Alternatively, the firmware instructions can be installed on PROM memory in the RF ports.

Figure 6 shows an arrangement for providing wireless access to the Internet using the RF port 50 of the present invention. Internet access over communications line 80 to modem 82 may be provided by cable, DSL or fiber optical transmission. RF port 50 may be provided with MAC firmware on PROM or may be configured with a bootloader program to download firmware from an ISP server. When installed in a home or office, mobile units 20 can associate with RF port 50 to initiate Internet access. The ISP server may perform the higher level MAC function, or they may be provided in RF port 50.

The mobile units 20 may be the personal computers 22 in a home or office with a WLAN adapter 24 as shown in Figure 2.

20 Figure 7 illustrates an example of communications formats that might be used in the various system embodiments of the present invention. The Figure 7 example assumes that the configuration includes a host 90 connected to a dedicated cell controller 14, which is likewise connected to RF port 18. It should be clearly understood that the logical cell controller functions may be performed in host 90, particularly in a simple system.

25 In the Figure 7 example host 90 sends message "A" having 100 data bytes via an

5 ethernet packet 100 to cell controller 14. Packet 100 has a destination address of the Mobile unit (M1), a source address of the host (H) and includes data (A). Cell controller 14 formats the data in 802.11 format with the destination corresponding to mobile unit (MU1) 20. The cell encapsulates this 802.11 packet with data A into an ethernet packet 104 addressed to RF port 1 (RF1) from the cell controller (CC).

10 RF port 18 receives the ethernet packet 104 from cell controller 14 and generates and sends an RF packet 112 in 802.11 format to mobile unit 20, including data A. It should be understood that 802.11 header generation can be provided at either the cell controller 14 or the RF port 18, but packet 104 must include mobile unit identification data either as an 802.11 header or otherwise to enable RF port 18 to generate the header. RF port 18 additionally  
15 performs the CRC computation and adds the result to the 802.11 packet 112.

A second message "B" having 1500 bytes of data is also shown as originating as Ethernet packet 102 from host 90 to cell controller 14. Cell controller fragments data message B into three fragments B1, B2 and B3 to accommodate the 500 byte data limit of 802.11 packets. These three fragments are sent as Ethernet packets 106, 108, 110 to RF port 18, which transmits  
20 RF signal packets 114, 116, 118 to mobile unit 20.

Reverse communication is similar. Message C has 100 bytes and is sent by mobile unit 20 to RF port 18 as 802.11 RF signal packet 200. RF port 18 encapsulates this message into ethernet packet 208 and sends it to cell controller 14, which extracts the destination information and data to provide ethernet message 216 to the host 90. A larger message D is sent  
25 as message fragments 202, 204, 206 to RF ports 18, relayed as ethernet packets 210, 212, 214 to

While there has been described what is believed to be claimed in the above-identified application those skilled in the art will recognize that other and further modifications may be made without departing from the scope of the invention and it is intended to claim all such changes and modifications as fall within the true scope of the invention.

I CLAIM:

1                   1. A system for providing wireless data communications between mobile units  
2 and a wired network, comprising:

3                   a plurality of RF ports having at least one data interface, said RF ports being  
4 arranged to receive formatted data signals at said data interface and transmit corresponding RF  
5 data signals and arranged to receive RF data signals and provide corresponding formatted data  
6 signals; and

7                   at least one cell controller, arranged to receive data signals from said wired  
8 network and to provide formatted data signals corresponding thereto to said data interface of said  
9 RF ports and to receive formatted data signals from said RF ports and to provide data signals  
10 corresponding thereto to said wired network, said cell controller controlling association of  
11 mobile units with one of said RF ports, providing formatted data signals for said mobile units to  
12 an associated RF port and receiving formatted data signals from said mobile unit from said  
13 associated RF port.

1                   2. In a wireless data communications network coupled to a data processing  
2 system, having a plurality of RF ports and mobile units, wherein said mobile units associate with  
3 one of said RF ports to conduct data communications with said data processing system, the  
4 improvement wherein said mobile units are assigned to one of said RF ports by a cell controller,  
5 and wherein said cell controller is arranged to receive first data communications from said data

1 processing system and to relay said data communications to an assigned RF port and to receive  
2 second data communications from said RF ports and relay said second data communications to  
3 said data processing system.

1 3. The improvement specified in Claim 2, wherein said cell controller, said RF  
2 data communications port and said data processing system are coupled to a switching hub.

1 4. A method for operating a wireless local area network having at least one RF  
2 port, a plurality of mobile units and a cell controller coupled to said RF port, comprising:  
3 operating said RF port to relay signals received from mobile units to said cell  
4 controller and to relay signals received from said cell controller to said mobile units, and  
5 operating said cell controller to control association of said mobile units with said  
6 RF port, including sending and receiving association signals between said RF port and said cell  
7 controller, and  
8 operating said cell controller to send messages to and from said mobile unit via  
9 said RF ports.

1 5. A method for operating a wireless local area network as specified in Claim 4,  
2 wherein signals are sent between said RF port and said cell controller using a first data protocol,  
3 and wherein signals are sent between said RF ports and said mobile units using a second data  
4 protocol, and wherein said signals between said RF port and said cell controllers comprise data

1 packets using said first data protocol encapsulating data packets using said second data protocol.

1 6. A method for operating a wireless local area network as specified in Claim 5  
2 wherein said first protocol is an Ethernet protocol.

1 7. A method for operating a wireless local area network as specified in Claim 6  
2 wherein said second protocol is an IEEE Standard 802.11 protocol.

1 8. In a mobile unit for use in a wireless data communications system, said mobile  
2 unit having a data processor and programs for said data processor and a wireless network adapter  
3 having a programmed processor and a radio module, the improvement wherein said programmed  
4 processor performs first communications processor functions including control of said radio  
5 module and said data processor operates under said programs to perform second communications  
6 processor functions, including association with a radio access location of said wireless data  
7 communications system.

1 9. The improvement specified in Claim 8 wherein said first communications  
2 processor functions include cyclic redundancy check functions and acknowledgment functions.



1           10. In a wireless data communications system for providing data communications  
2 following a standardized protocol, said protocol including association of mobile units with radio  
3 access locations, the improvement wherein there is provided at least one RF port at a radio access  
4 location, said RF port comprising a radio module and an RF port processor in data  
5 communications with a programmed computer, wherein said RF port processor performs first  
6 functions of said standardized protocol and said programmed computer performs second  
7 functions of said standardized protocol, including said association of mobile units with said radio  
8 access location.

1           11. The improvement specified in Claim 10, wherein said RF port further  
2 includes a read-only memory and a random access memory, and wherein said read-only memory  
3 includes a bootloader program, wherein said RF port processor is arranged to operate under said  
4 bootloader program to download instructions from said programmed computer and to store said  
5 instructions in said random access memory, and wherein said RF port processor operates under  
6 control of said downloaded instructions to perform said first functions.

1           12. The improvement specified in Claim 10. wherein said standardized protocol  
2 includes cyclic redundancy check functions, and wherein said first functions include said cyclic  
3 redundancy check functions.

1           13. The improvement specified in Claim 10, wherein said standardized protocol  
2 includes encryption/decryption functions and wherein said first functions include said  
3 encryption/decryption functions.

1           14. The improvement specified in Claim 10, wherein said standardized protocol  
2 includes encryption/decryption functions and wherein said second functions include said  
3 encryption/decryption functions.

1           15. An RF port for use in a wireless data communications system comprising a  
2 radio module, having a data interface and a transmitter/receiver for wireless data  
3 communications, and a digital signal processor, having first and second data communications  
4 ports, random access memory and read-only memory, wherein said second data communications  
5 port is coupled to said data interface of said radio module, wherein said read-only memory is  
6 provided with a bootloader program for controlling said digital signal processor to load program  
7 instructions to said random access memory via said first communications port.

1           16. An RF port as specified in Claim 15, wherein said digital processor has a  
2 third data communications port and wherein said third data communications ports is coupled to  
3 said data interface of said radio module.

1 17. An RF port as specified in Claim 16, wherein said second and third  
2 communications ports of said digital processor comprise serial ports.

1 18. An RF port as specified in Claim 15, wherein said first communications port  
2 comprises a parallel port.

1 19. An RF port as specified in Claim 18 wherein said parallel port is coupled to  
2 an Ethernet controller.

1 20. A method for operating an RF port having a radio module, a digital processor,  
2 random access memory and read-only memory, comprising storing a bootloader program in said  
3 read-only memory, operating said digital processor to download instructions from a computer to  
4 said random access memory using said bootloader program and operating said RF port under said  
5 downloaded instructions to send and receive messages using said radio module.

1 21. A method as specified in Claim 20, wherein said step of operating said RF  
2 port comprises receiving messages from said computer including protocol message portions for  
3 RF message transmission, and transmitting said message including said protocol message  
4 portions as an RF signal.

1           22. A method as specified in Claim 20, wherein said step of operating said RF  
2 port comprises receiving RF messages having an RF protocol and sending said RF messages to  
3 said computer as data signals encapsulated in a further message protocol.

1           23. A method as specified in Claim 22 further comprising interpreting said RF  
2 protocol using said downloaded instructions and sending said RF messages to said computer  
3 only if said RF messages include an identification of said RF port.

1           24. A method as specified in Claim 20 wherein said downloaded instructions  
2 configure said computer and said RF port to operate as an access point for communication with  
3 mobile units.

1           25. A method as specified in Claim 24 wherein said computer is operated to  
2 control association of said mobile units with said computer and RF port.

1           26. A method as specified in Claim 20 wherein said downloaded instructions  
2 configure said computer and said RF port to operate as a mobile unit for communications with  
3 access points.

1           27. A method as specified in Claim 20 wherein said downloaded instructions  
2 configure said computer and said RF port to operate as either an access point or a mobile unit

1 under control instructions from said computer.

2  
3 28. A method for transmitting signals having a wireless signal format using an  
4 RF port having a wired network interface, a data processor and an RF module, comprising  
5 providing signals to said wired network interface having wireless address data and message data  
6 within a data packet addressed to said RF port using a protocol for said wired network, operating  
7 said processor to provide wireless data signals having said wireless signal format for said address  
8 data and said message data to said RF module and operating said RF module to transmit said  
9 wireless data signals as an RF signal modulated with said wireless signal format.

10  
11 29. A method for transmitting signals having a wireless signals format using an  
12 RF port having an Ethernet interface, a data processor and an RF module, comprising providing  
13 an Ethernet data packet to said Ethernet interface, said Ethernet data packet encapsulating as data  
14 a data message having said wireless signal format, operating said data processor to provide said  
15 data message to said RF module, and operating said RF module to transmit said data message as  
16 an RF signal.

1 30. A method as specified in Claim 29 further comprising operating said data  
2 processor to perform a cyclic redundancy computation on said data message and adding the  
3 result thereof to said data message.

1           31. A method as specified in Claim 29 further comprising operating said data  
2 processor to control said radio module.

3  
4           32. A method for receiving signals having a wireless signal format including  
5 wireless address data and message data at an RF port having a wired network interface, a data  
6 processor and an RF module, comprising operating said RF module to receive RF signals having  
7 said wireless signal format, operating said data processor to receive wireless data signals from  
8 said RF module and provide data signals to said wired network interface comprising a data  
9 packet having a source address corresponding to said RF port using a protocol for said wired  
10 network, said data packet including said wireless address data and said message data.

1           33. A method for receiving RF message signals having a wireless signal format  
2 including an address data format and message data using an RF port having an Ethernet interface,  
3 a data processor and an RF module, comprising receiving said RF message signals in said RF  
4 module and providing said signals as data signals to said data processor, operating said data  
5 processor to interpret address data in said data signals and, in dependence on said address data  
6 encapsulating said message data and address data in an Ethernet packet and providing said  
7 Ethernet packet to said Ethernet interface.

1           34. A method as specified in Claim 33 wherein said data processor is operated to  
2 encapsulated said address data in said Ethernet packet.

1           35. A method as specified in Claim 33 wherein said data processor is further  
2 operated to perform a cyclic redundancy computation on said message data and to compare the  
3 result thereof with corresponding data received in said data signals.  
4

5           36. A method as specified in Claim 33, further comprising operating said data  
6 processor to control said radio module.

1           37. A simplified wireless local area network system comprising:  
2 a computer having a data processor and a memory;  
3 an RF port having an RF port data processor, an RF module and a data  
4 communications interface coupled to said computer;  
5 a first program in said memory of said computer for operating said computer data  
6 processor to perform first wireless data communications functions, said functions including  
7 association with mobile units; and  
8 a second program for operating said RF port data processor to perform second  
9 wireless data communications functions.

1           38. A system as specified in Claim 37 wherein said second program operates said  
2 RF port data processor to perform second wireless data communications functions, including  
3 control of said RF module.

1                   39. A system as specified in Claim 37 wherein said second program operates said  
2 RF port data processor to perform second wireless data communications functions, including  
3 cyclic redundancy check functions.

1                   40. A system as specified in Claim 37 wherein said second program is stored in  
2 said computer memory and wherein said RF port data processor is arranged to download said  
3 second program.

1                   41. A wireless access device for providing wireless access to a communication  
2 system, comprising a modem for sending and receiving data messages on said communications  
3 system and an RF port, comprising a data interface coupled to said modem, a data processor and  
4 an RF module, said processor being programmed to receive data messages from said modem, to  
5 format said messages for wireless data communications and to provide said formatted messages  
6 to said RF module for transmission by RF data signals to at least one remote station, and to  
7 receive RF data signals from said at least one remote station, and to provide data messages to  
8 said modem to be sent on said communications system.

1                   42. A wireless access device as specified in Claim 40 wherein said  
2 communications system is a DSL communications system connected to the Internet, and wherein  
3 said modem comprises a DSL modem.



1                   43. A wireless access device as specified in Claim 40 wherein said  
2                   communications system is a two-way cable communications system connected to the Internet,  
3                   and wherein said modem comprises a cable modem.

1                   44. A wireless access device as specified in Claim 42 wherein said  
2                   communication system comprises a fiber optic system, and wherein said modem comprises a  
3                   fiber optical modem.

1                   45. A method for providing wireless access to the Internet, comprising providing  
2                   a modem coupled to the Internet and having a data communications interface connected to an RF  
3                   port, configuring said RF port for wireless data communication to a mobile unit having a  
4                   predetermined wireless communications address, and providing at least one mobile unit  
5                   configured with said predetermined wireless communications address for conducting RF data  
6                   communications with said RF port, said RF port being arranged to relay communications  
7                   between said mobile unit and said modem.

1                   46. The method specified in Claim 44 wherein said step of providing said mobile  
2                   unit, comprises providing a computer having an RF port.

1 47. A system for sending and receiving data messages to at least one mobile unit,  
2 comprising:

3 at least one RF port having an RF module for sending and receiving data  
4 messages to said at least one mobile unit using a first RF communications protocol, having a  
5 wired interface for sending and receiving data messages using a wired communications protocol,  
6 and a programmed processor for relaying data messages received on said wired interface using  
7 said RF communications protocol and for relaying data messages received by said RF module  
8 using said wired communications protocol; and

9 at least one cell controller for sending data messages to said wired interface of  
10 said RF port and for receiving data messages from said RF port using said wired communications  
11 protocol.

12 48. A system as specified in claim 47, wherein there are provided a plurality of  
13 said RF ports, and wherein said cell controller is arranged to address said data messages to said  
14 RF ports using said wired communication protocol.

15 49. A system as specified in claim 48 wherein said at least one mobile unit is  
16 associated with one of said RF ports, and wherein said processor is programmed to interpret  
17 source address data received in said RF communications protocol and for relaying a received  
18 message using said wired communications protocol only if said source address data corresponds  
19 to a mobile unit associated with said RF port.

1           50. A system as specified in claim 47 wherein said cell controller is arranged to  
2 provide messages to said RF port comprising mobile unit address data and message data  
3 encapsulated in a data packet following said wired communications protocol.

1           51. A system as specified in claim 50 wherein said cell controller is arranged to  
2 provide said mobile unit address data and said message data in said RF communications protocol  
3 encapsulated in said wired communications format.

1           52. A system as specified in claim 47 wherein said RF port is arranged to  
2 encapsulate messages received by said RF module in a data packet using said wired  
3 communication protocol.

1           53. A method for operating a wireless data communication system having at least  
2 one cell controller, at least one RF port and at least one mobile unit, comprising sending a first  
3 data message for said mobile unit from said cell controller to said RF port using a wired  
4 communication protocol, relaying said first message in said RF port using an RF communication  
5 protocol and sending said first message by radio signal from said RF port to said mobile unit.

1           54. The method specified in claim 53 wherein there are a plurality of RF ports  
2 and wherein said mobile unit is associated with one of said RF ports, and wherein said first data

1 message is addressed to said RF port associated with said mobile unit.

1 55. The method specified in claim 53 wherein sending said first data message to  
2 said RF port comprises sending address data and message data encapsulated in a data packet  
3 using said wired communications protocol.

1 56. The method specified in claim 55 wherein said encapsulated address data and  
2 message data is formatted according to said RF communications protocol.

1 57. The method specified in claim 53, further comprising sending a second data  
2 message from said mobile unit to said RF port by radio signal using said RF communication  
3 protocol, and relaying said second data message using said wired communication protocol from  
4 said RF port to said cell controller.

1 58. A method for operating a wireless data communications system having at  
2 least one cell controller, at least one RF port and at least one mobile unit, comprising sending a  
3 data message by radio signal from said mobile unit to said RF port using an RF communications  
4 protocol, and relaying said message using a wired communication protocol from said RF port to  
5 said cell controller.

1 59. The method specified in claim 58 wherein said relaying comprises

- 1 encapsulating said RF communications protocol message in a data packet using said wired
- 2 communications protocol.

004420 46332360

**ABSTRACT**

5

A wireless local area network is provided with simplified RF ports which are configured to provide lower level media access control functions. Higher level media access control functions are provided in a cell controller, which may service one or more RF ports. Mobile units can also be configured with the higher level media access control functions being performed in a host processor.

004760 26932560

0027ED 26982560




FIG. 1




FIG. 2








FIG. 4




FIG. 5




FIG. 6




FIG. 7